

P O T T E R Y B A R N

HAYDEN TUBE SCONCE SINGLE

Assembly Instructions

Important Safety Instructions:

- These instructions are provided for your safety. It is important that they are read carefully and completely before installing the chandelier.
- **THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODES BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED.**
- **We strongly recommend that a professional electrician install all direct wire fixtures.**
- This fixture has been rated for up to **(1) 60-watt TYPE B BULB** (not included). To avoid the risk of fire, do not exceed the recommended wattage.
- The lighting fixture is meant for indoor use, **SUITABLE FOR EITHER DRY OR DAMP LOCATIONS**. It must be connected only to 3-wire, single-phase electrical supply systems (provided with Ground wire or equivalent protection system).
- **SAVE THESE INSTRUCTIONS.**

WARNING:

- **To reduce the risk of fire, electrical shock or personal injury, always turn off light fixture and allow it to cool prior to replacing light bulb.**
- **Do not touch bulb when fixture is turned on. Do not look directly at lit bulb.**
- **Keep flammable materials away from lit bulb.**

Pre-assembly:

- Remove all parts and hardware from box along with any plastic protective packaging. Do not discard any contents until after assembly is complete to avoid accidentally discarding small parts or hardware.
- For your safety and convenience, assembly by two people is recommended.

Parts Enclosed:

- (1) Mounting plate (B)
- (1) Canopy (F)
- (1) Lamp Cup (H)
- (1) Glass Shade (K)
- (1) Metal Ring (J)
- (1) Socket(I)
- (1) Socket Ring (L)

Hardware Included:

- (2) Drywall Anchor (A)
- (2) Drywall Screw (C)
- (3) Wire cap (E)
- (2) Canopy Screw (G)
- (1) Tooling (N)

Tools required for assembly:

- Electrical tape
- Screwdriver
- Wire cutters

To Assemble:

1. SHUT OFF THE MAIN ELECTRICAL SUPPLY FROM THE MAIN FUSE BOX/CIRCUIT BREAKER.
2. Carefully unpack all fixture parts and hardware and lay out on a clear workspace.
3. Insert (1) 60-watt Type B bulbs (not included) into the socket .DO NOT EXCEED SPECIFIED

WATTAGE

4. Unscrew the Socket Ring(L) from the Socket (I)
5. Inset Glass Shade(K) into the Metal Ring(J) and take the Glass shade onto the Socket (I)
6. Screw the Socket Ring (L) onto the Socket(I) by Tooling (N)
7. Carefully inspect the chandelier's fixture wires. The NEUTRAL FIXTURE WIRE is white or marked "N". The HOT FIXTURE WIRE is black or marked "L". The yellow-green or bare wire is the GROUND WIRE.
8. Attach the GROUND WIRE from the fixture to the GROUND JUNCTION BOX WIRE from the outlet (usually green or bare wire). Fasten each together with a Wire Cap (E) and wrap the connection with electrical tape. Be sure that no wire strands are exposed. **IT IS IMPERATIVE THAT THE OUTLET BOX IN YOUR HOME BE PROPERLY GROUNDED.**
9. Connect the NEUTRAL FIXTURE WIRE to the NEUTRAL JUNCTION BOX WIRE (white). Fasten each together with a Wire Cap (E) and wrap the connection with electrical tape. Be sure no wire strands are exposed.
10. Connect the HOT FIXTURE WIRE to the HOT JUNCTION BOX WIRE (black). Fasten each together with a Wire Cap (E) and wrap the connection with electrical tape. Be sure no wire strands are exposed. **DO NOT REVERSE THE HOT AND NEUTRAL CONNECTIONS OR SAFETY WILL BE COMPROMISED.**
11. Gently tuck the wire connections neatly into the **wall outlet** box
12. Screw the Drywall Anchor (A) Into the Wall, the vertical distance of Two Drywall Anchors(A) is Same as the distance of the Mounting Plate's(A) two holes
13. Attach the mounting plate (B) onto the Drywall Anchor(A) and align the hole in the mounting plate (B) with the Drywall Anchor(A), Tighten Drywall screws(C) with a screwdriver.
14. Pull canopy (F) up over the mounting plate (B), align the hole in the mounting plate with the hole in the canopy.
15. Screws Canopy screws (G) and tighten with a screwdriver

Completing the Assembly:







1. Insert (1) 60-watt Type B bulbs (not included) into the socket .DO NOT EXCEED SPECIFIED WATTAGE.
2. Restore power to junction box and test fixture.
3. Assembly is complete.

Care Instructions:

- Wipe clean using a soft, dry cloth or static duster.
- Always avoid the use of harsh chemicals and abrasives to clean fixture as they may damage the finish.

WARNING:

- This lighting fixture contains lead, a chemical know to the State of California to cause cancer, birth defects and other reproductive harm. Wash hands after installing, handling, cleaning or otherwise touching this light fixture.

E		2x
A		2x
C		2x
G		2x
D		1x
N		1x

